

ELECTRIC GUITAR

Job	Materials	Price	Process overview	Turn around (days)
Guitar\bass Full set tuning machine swap w/out hole fill	Full set tuning machines	25	No holes drilled, string removal and reinstalled, tuning. Body/headstock wipe down	1-2
Guitar\bass Full set tuning machine swap w/ mod	Full set tuning machines	40	New screw holes drilled and or insert holes expanded. String removal and reinstall. Overnight only	1-2
Guitar tele/Strat style saddle replacement single	Guitar saddle	15	String removal/reinstall tuning	Same day or next
bass saddle replacement single	Bass saddle	15	String removal/reinstall tuning	Same day or next
Guitar string tree install	Tree	25	De-tuning, install tree, tune	1-2
Guitar Strat style trem swap	Trem system strings	90	Removal of current system to replace with new system, includes setup, not saving existing strings, no routing, system must fit.	4-5
Guitar Strat style bridge swap	Bridge/ strings	60	Swap of bridge or trem block only	3-4
Guitar hard tail, vibrato trem install	Trem /strings	90	Install of bigsdy style trem to a hardtail, must be sure the part matches top of guitar (flat/arch top) no routing	5-6
Guitar nut file	None	30	File/ change existing nut slots	1-2
Guitar nut replacement	Nut	45	Removal of existing nut. Fit new nut to guitar, glue and clamp. 24hrs needed	2-4
Guitar Strap lock install	Strap LOCK	25	Removal of existing strap button, hole resizing if needed, install new button	1-2
Guitar neck swap	Neck	65	Install new neck, setup required	4-5
Guitar tune o matic style bridge receiver replacement	Receivers	60	Existing receivers removed and new ones installed, no routing, must fit	3-4
Guitar tune o matic bridge replacement	Bridge	40	Bridge must match radius of fretboard	

ELECTRONICS

Job	Materials	Price (labor)	Process overview	Turn around (days)
Electronics diagnostics		60-1.5 hr	Voltmeter testing each part of circuit individually no same day	4-5
Pick guard swap	Pick guard/customer parts	60	Remove strings remove electronic parts and de solder body connections, install parts to new pickguard clean solders, add heat shrink as needed	3-4
Pick up swap(per)	Pick up price	60	Existing pick up removal/ new install solder or solderless. Clean solders add heat shrink where needed Pickguard/string removal required.	4-5
Guitar S1 switch	Switch	50	Wired in various ways, cust preference, non refundable if no preference given	4-5
Guitar various switch install		30-60	Includes solderless parts/ various dpdt switches and jazz master/ jaguar style switches	2-4
Guitar 3way toggle switch replacement	Switch	45	Remove existing switch/install clean solders add heat shrink as needed	2-3
5 way switch replacement	Switch	45	Remove existing part and replace with new part. Clean all existing solders as needed and add heat shrink as needed	2-3
Out put jack replacement	Output jack	30	Remove existing out put jack and install new one, clean solders	1-2
Potentiometer replacement	Part	30	Remove existing part and replace. Clean all solders as needed ad heat shrink as needed	2-3
Guitar treble bleed	Various components	55	Added to tone pot (varies for every guitar configuration)	4-5
Guitar circuit modification		75	Phase switch, split coil.	4-5